

GASOLINE GENERATOR



Model		NK3500W-SE		NK3800W-SE		NK6500W-SE	
Voltage	V	220	120/220	220	120/220	220	120/220
Frequency	Hz	50	60	50	60	50	60
Rated Output Power	kW	2.5	2.8	3	3.3	5	5.5
Max. Output Power	kW	2.8	3	3.3	3.5	5.5	6
Phase		1	1	1	1	1	1
Power Factor COS	∅	1.0	1.0	1.0	1.0	1.0	1.0
Excitation Mode		Brush (AVR)		Brush (AVR)		Brush (AVR)	
DC Output	V/Amps	12/8.3	12/8.3	12/8.3	12/8.3	12/8.3	12/8.3
Noise level (at 7m)	dB	≤65	≤65	≤65	≤65	≤67	≤67
Engine model		NK168FB	NK168FB	NK170FB	NK170FB	NK188F	NK188F
Max. Output Power	HP	6.5	6.5	7.5	7.5	13	13
Bore*Stroke	mm	68*54	68*54	70*58	70*58	88*64	88*64
Speed	rpm	3000	3600	3000	3600	3000	3600
Displacement	cc	196	196	223	223	389	389
Start system		Electric		Electric		Electric	
Fuel Capacity	L	16	16	16	16	25	25
Overall Dimension	mm	900x552x740		900x552x740		950x570x780	
Weight	Kg	110		112		144	
20GP/40GP/40HQ Loading	pcs	64/140/160		64/140/160		74/164/190	
Emission Compliance		Available also in Stage V					