

GASOLINE GENERATOR



| Model | | NK3800W-SE | |
|------------------------|--------|----------------------------------|-----------|
| Voltage | V | 220 | 120/220 |
| Frequency | Hz | 50 | 60 |
| Rated Output Power | kW | 3 | 3.3 |
| Max. Output Power | kW | 3.3 | 3.5 |
| Phase | | 1 | 1 |
| Power Factor COS | ∅ | 1.0 | 1.0 |
| Excitation Mode | | Brush (AVR) | |
| DC Output | V/Amps | 12/8.3 | 12/8.3 |
| Noise level (at 7m) | dB | ≤65 | ≤65 |
| Engine model | | NK170FB | NK170FB |
| Max. Output Power | HP | 7.5 | 7.5 |
| Bore*Stroke | mm | 70*58 | 70*58 |
| Speed | rpm | 3000 | 3600 |
| Displacement | cc | 223 | 223 |
| Start system | | Electric | |
| Fuel Capacity | L | 16 | 16 |
| Overall Dimension | mm | 900x552x740 | |
| Weight | Kg | 112 | |
| 20GP/40GP/40HQ Loading | pcs | 64/140/160 | |
| Emission Compliance | | Available also in Stage V | |

Available also in three-phase